



F&F Filipowski L.P.
Konstantynowska 79/81, 95-200 Pabianice, POLAND
phone/fax (+48 42) 215 23 83 / (+48 42) 227 09 71
www.fif.com.pl; e-mail: biuro@fif.com.pl

WN-723

Voltage indicator,
3-phase



Do not dispose of this device in the trash along with other waste! According to the Law on Waste, electro coming from households free of charge and can give any amount to up to that end point of collection, as well as to store the occasion of the purchase of new equipment (in accordance with the principle of old-for-new, regardless of brand). Electro thrown in the trash or abandoned in nature, pose a threat to the environment and human health.




Purpose

The WN-723 voltage indicator is used for continuous measurement and optical visualisation of the voltage value in the three-phase network.


Functioning

The indicated voltage range is 180 V to 270 V with a reading accuracy of 10 V. The illumination of the LEDs indicates the voltage value described on its height. Voltage values between 190 V and 260 V are indicated by the lighting of the green LEDs. Extreme values of 180 V and 270 V are indicated by a red LED. Voltage lower than 180 V is indicated by the flashing of the red 180 V LED. Voltage higher than 270 volts is indicated by flashing of the LED at the top, or in „bar” mode by flashing of the entire bargraph. The unit can operate in „bar” or „single diode” mode. The selection is made by shorting (or not) leads 7-8.

Operating modes



„Bar“ mode,
connection without jumper




Single diode“ mode,
jumper connection

Mounting

1. Disconnect the power supply.
2. Install the indicator on the rail in the distribution board.
3. Connect the power wires according to the diagram.
4. Select the device mode (terminals 7-8).
5. Switch on the power supply and verify that the device is working correctly.

Wiring diagram



Technical data

power supply	3×230 V+N
voltage indicator	3× (10×LED)
indication range	180÷270 V
working mode	bar mode or single diode mode
measurement error	<2%
reading accuracy	10 V
power consumption	<1 W
working temperature	-25÷50°C

terminal	2.5 mm ² screw terminals (cord) 4.0 mm ² screw terminals (wire)
tightening torque	0.5 Nm
dimensions	2 modules (35 mm)
mounting	on TH-35 rail
ingress protection	IP20

Warranty

F&F products are covered by a 24-month warranty from the date of purchase. The warranty is only valid with proof of purchase. Contact your dealer or contact us directly.

CE declaration

F&F Filipowski L.P. declares that the device is in conformity with the essential requirements of The Low Voltage Directive (LVD) 2014/35/EU and the Electromagnetic Compatibility (EMC) Directive 2014/30/UE.

The CE Declaration of Conformity, along with the references to the standards in relation to which conformity is declared, can be found www.fif.com.pl on the product subpage.